

TP-Link Archer D2 Fibre configuration

Logging into the gateway:

1. Ensure your device is connected to the Router (preferably via cable)
2. Open a web browser
3. Type the following in the address bar at the top: **192.168.1.1**
4. Default Username: **admin**
5. Default Password: **admin**
6. This should then give access to the routers user interface. *
** (If the password is incorrect you will need to Factory Reset the router by pushing the Inset Reset button on the back for 10 seconds) **

How to add correct settings for the NOW network:

1. From the top menu select: **Advanced**
2. From the left menu select: **Operation Mode**
3. Select: **Save** (the router will now reboot)
4. From the top menu select: **Basic**
5. From the left menu select: **Internet**

Ensure the following settings are changed:

1. ISP List: **Other**
2. Connection Type: **PPPoE**
3. Username: **(Account ID)@nownz.co.nz**
4. Password: **password**
5. Select: **Save**

The router will now reboot once more. When it reconnects, you should be connected to Fibre!

If your internet connection is still not working, give NOW Technical Support a call.



