

## TP-Link TD-W8960 Fibre configuration

### Logging into the gateway:

1. Ensure your device is connected to the Router (preferably via cable)
2. Open a web browser
3. Type the following in the address bar at the top: **192.168.1.1**
4. Default Username: **admin**
5. Default Password: **admin**
6. This should then give access to the routers user interface. \*  
\*\* (If the password is incorrect you will need to Factory Reset the router by pushing the Inset Reset button on the back for 10 seconds) \*\*

### How to add correct settings for the NOW network:

1. From the menu on the left select: **Advanced Setup**
2. From the sub-menu select: **Layer 2 Interface**
3. And then: **ETH Interface**
4. In the page: **Remove any existing ETH Interfaces**
5. Select: **Add**
6. Select an ETH Interface of: **ETH3/LAN4**
7. Click: **Apply/Save**
8. From the menu on the left select: **WAN Service**

Ensure the following settings are changed:

1. PPP Username: **(your NOW account ID)@nownz.co.nz**
2. PPP Password: **password**
3. PPPoE Service Name: **(Left Blank)**
4. Authentication Method: **Auto**
5. MTU: **1492**
6. Click: **Next**

Click through next couple of pages

1. Select: **Save/Apply**

You should now be connected to Fibre!

If your internet connection is still not working, give NOW Technical Support a call.



300Mbps Wireless N ADSL2+ Modem Router  
Model No. TD-W8960N

Device Info  
Quick Setup  
Advanced Setup  
+ Layer2 Interface  
- WAN Service  
+ MAC Clone  
+ LAN  
+ NAT  
+ Security  
+ Parental Control  
+ Quality of Service  
+ Bandwidth Control  
+ Routing  
+ DNS  
+ DSL  
+ UPnP  
+ Interface Grouping  
+ IP Tunnel  
+ IPSec  
+ Multicast  
Wireless  
Guest Network  
Diagnostics  
Management  
Logout

### PPP Username and Password

PPP usually requires that you have a user name and password to establish your connection. In the boxes below, enter the user name and password that your ISP has provided to you.

PPP Username:   
 PPP Password:

PPPoE Service Name:   
 Authentication Method:   
 MTU (bytes):  (The default is 1480, do not change unless necessary.)

Enable Fullcone NAT  
 Dial on demand (with idle timeout timer)  
 Use Static IPv4 Address  
 Enable PPP Debug Mode  
 Bridge PPPoE Frames Between WAN and Local Ports

Multicast Proxy  
 Enable IGMP Multicast Proxy

Back

300Mbps Wireless N ADSL2+ Modem Router  
Model No. TD-W8960N

Device Info  
Quick Setup  
Advanced Setup  
+ Layer2 Interface  
+ ATM Interface  
+ ETH Interface  
+ WAN Service  
+ MAC Clone  
+ LAN  
+ NAT  
+ Security  
+ Parental Control  
+ Quality of Service  
+ Bandwidth Control

### ETH WAN Interface Configuration

Choose Add, or Remove to configure ETH WAN interfaces.  
Allow one ETH as layer 2 wan interface.

| Interface/(Name)   | Connection Mode | Remove |
|--|-----------------|--------|
| <input type="button" value="Add"/> <input type="button" value="Remove"/> |                 |        |

300Mbps Wireless N ADSL2+ Modem Router  
Model No. TD-W8960N

Device Info  
Quick Setup  
Advanced Setup  
+ Layer2 Interface  
+ WAN Service  
+ MAC Clone  
+ LAN  
+ NAT  
+ Security  
+ Parental Control  
+ Quality of Service  
+ Bandwidth Control

### Wide Area Network (WAN) Service Setup

Choose Add, Remove or Edit to configure a WAN service over a selected interface.

| Interface | Description | Type  | Vlan8021p | VlanMuxId | Igmp    | NAT     | Firewall | IPv6     | Mid      | Remove                   | Edit                                |
|-----------|-------------|-------|-----------|-----------|---------|---------|----------|----------|----------|--------------------------|-------------------------------------|
| ppp0a0    | ppp0a_0_100 | PPPoA | N/A       | N/A       | Enabled | Enabled | Enabled  | Disabled | Disabled | <input type="checkbox"/> | <input type="button" value="Edit"/> |
| ppp1      | Now NZ Fore | PPPoE | N/A       | N/A       | Enabled | Enabled | Enabled  | Disabled | Disabled | <input type="checkbox"/> | <input type="button" value="Edit"/> |