

Fritz box 7360 Fibre configuration

Ensure the Router is connected from **LAN1** on **Router** to **GE1** on **ONT**.

Log into the gateway:

1. Ensure your device is connected to the router (preferably via cable)
2. Open a Web browser
3. Type the following in the address bar at the top: **fritz.box**
4. If the first time you have logged in, then it will not require a username.
5. Select: **Skip This Step** and Continue
6. This should then give access to the routers user interface.

How to add correct settings for the NOW network:

1. From the menu on the left select: **Internet**
2. From the sub-menu select **Account Information**
3. In the page locate the **Internet Connection tab**

Ensure the following settings are changed:

1. Internet Service Provider: **Other**
2. Name: **Now NZ**
3. Connect Via: **External Modem or Router**
4. Operating Mode: **Make Own Connection to the Internet**
5. Is Account Information Required?: **Yes**
6. Username: **(your NOW account ID)@nownz.co.nz**
7. Password: **password**
8. Upstream: **320000kbit/s**
9. Downstream: **320000kbit/s**
10. Select: **Change Connection Settings**
11. Maintain Permanently: **Ticked**
12. Use VLAN for Internet Access: **Unticked**
13. Check the Internet connection after "Apply": Ticked
14. Click: Apply
15. Click: Submit

You should now be connected to Fibre!

If you have no internet access, give NOW Technical Support a call.



FRITZ! **FRITZ!Box 7360**

FRITZ!Box | FRITZ!NAS | MyFRITZ! | ?

Overview
Internet
 Online Monitor
Account Information
 Filters
 Permit Access
 MyFRITZ!
 DSL Information
Telephony
Home Network
WLAN
DECT
Diagnostics
System

Account Information

Internet Connection | IPv6 | LISP | DNS server

On this page you enter the data of your Internet connection, and can adjust the connection to special circumstances if needed.

Internet service provider
 Select your Internet service provider:
 Internet service provider: Other Internet service provider
 Name: Now NZ

Connect via
 Specify how the Internet connection should be established.
 Connection to a DSL line
 Select this kind of connection when the FRITZ!Box is connected to your DSL line using the DSL cable. The DSL modem integrated in the FRITZ!Box is used for the Internet connection.
 Connecting to a cable modem (cable connection)
 Select this kind of connection if the "LAN 1" port of the FRITZ!Box is connected to a cable modem that establishes the Internet connection.
 External Modem or Router
 Select this kind of connection if the "LAN 1" port of the FRITZ!Box is connected to an already existing external modem or router.

Operating Mode
 Specify whether the FRITZ!Box connects to the Internet itself or shares an existing Internet connection.
 Make own connection to the Internet
 The FRITZ!Box disposes over its own IP address range. The firewall remains enabled.
 Share existing Internet connection in the network (IP client mode)
 The FRITZ!Box becomes part of the existing network and takes over this IP address range. The firewall of the FRITZ!Box is disabled.

Account Information

is account information required?
 Yes
 No

Enter the Internet account information you received from your Internet service provider.

User name: (your NOW ID)@nownz.co.nz
 Password: password

Connection Settings
 The connection settings are already set to the most frequently used values. You can change these values if needed.

Data Throughput
 Enter the speed of your line. These values are required to secure the prioritization of the network devices.

Upstream: 320000 kbit/s
 Downstream: 320000 kbit/s

Change connection settings ▲

Internet connection
 Maintain permanently (recommended for flat rates)
 Delay disconnection by provider to the period between 3 - 4
 Clear idle connection (recommended for time- or usage-based rates)
 Clear automatically after 300 seconds

VLAN Settings
 Please note that a VLAN ID is required only in special cases. The required ID was supplied by your Internet service provider.
 Use VLAN for Internet access
 VLAN-ID: _____

Check the Internet connection after "Apply" has been clicked

Apply Cancel

View: Advanced | Contents | Manual | avm.de