

Netgear D6220 Fibre configuration

Log into the Gateway:

1. Connect your device to the router (preferably hardwired)
2. Open a Web Browser
3. In the web browsers address bar type: `www.routerlogin.net`
4. Default Username: admin
5. Default Password: password or Admin (this may have been changed to your own)*
6. This should then give access to the routers user interface.

*If the default password does not work and you cannot remember the changed password, you may need to factory reset the router by hushing and holding the inset reset button for 10 seconds.

How to add correct settings for the NOW network:

How to change the correct settings:

1. From the Advanced menu select: **Setup**
2. From the sub-menu select: **WAN Setup**
 - a. WAN Preference: Must Use **Ethernet WAN**
 - b. This will now reboot the router
3. From the Advanced tab select **Setup**
4. From the sub-menu select: **Internet Setup**
 - c. Select Country: **NZ**
 - d. Select Internet Service Provider: **Other**
 - e. Enable This Interface: **Ticked**
 - f. Use VLAN ID: **Unticked**
 - g. Does your internet require a login: **Yes**
 - h. Internet Service Provider: **PPPoE**
 - i. Login: (your NOW account ID)`@nownz.co.nz`
 - j. Password: **password**
 - k. Connection Mode: **Always On**
 - l. Click: **Apply** (top of page)
 - m. This will again reboot the router

You should now be connected on Fibre!

See screenshots on following page:



BASIC **ADVANCED** Auto ▾

ADVANCED Home **WAN Setup** Cancel Apply ▶

Setup Wizard

WPS Wizard

Setup

Internet Setup
Wireless Setup
Guest Network
WAN Setup
LAN Setup
QoS Setup

WAN Preference Must use Ethernet WAN ▾

Disable Port Scan and DoS Protection

Default DMZ Server 192 168 1

Respond to Ping on Internet Port

Disable IGMP Proxying

MTU Size(in bytes) 1500

NAT Filtering Secured Open

Disable SIP ALG

Internet Setup Test Cancel Apply ▶

Select Country NZ ▾

Select Internet Service Provider Other ▾

Transfer Mode PTM ▾

DSL Mode VDSL2 ▾

Internet ▾

Enable This Interface

Multiplexing Method VC-Based ▾

VPI 8

VCI 35

Use VLANID

Priority(0~7) 0

Does your Internet connection require a login?

Yes

No

Internet Service Provider PPPoE ▾

Login (your NOW ID)@nowmz.co.nz

Password password

Service Name (If Required)

Connection Mode Always On ▾

Idle Timeout(In Minutes) 5