

Vodafone Huawei HG659 Fibre configuration

Logging into the gateway:

1. Ensure your device is connected to the Router (preferably via cable)
2. Open a web browser
3. Type the following in the address bar at the top: **192.168.1.1**
4. Do not use the default Vodafone/Vodafone login details.
5. Default Username: **Admin** (case sensitive)
6. Default Password: (Dependant on Software Version Number)
 - a. To check the Software Version Number click the Status Information drop-box at the base of the login page. The Software/Firmware Version number should be listed here
7. For Version ending in B013 the password is: **VF-NZhG659**
8. For Version ending in B019 or higher: **@(followed by the last 8 digits of the routers Serial Number) ***
9. This should then give access to the routers user interface.**

* The Serial Number can be found on the sticker on the back of your router.

** (If the password is incorrect you will need to Factory Reset the router by pushing the Inset Reset button on the back for 10 seconds)

How to add correct settings for the NOW network:

1. From the menu along the top of page select: **Internet**
2. From the menu on the left select: **Internet Settings**
3. On the main page locate: **Internet_TR069_ETH_VID10**
4. Beneath this option select: **Edit**

Ensure the following settings are changed:

1. Enable Connection: **Ticked**
2. Service Type: tick **Internet (TR069 and Voice not ticked)**
3. Connection Type: **IP Routing (PPP)**
4. MRU: **1492**
5. MSS: **0**
6. NAT Type: **NAPT**
7. Enable VLAN: **Unticked**
8. PPP Authentication Mode: **Auto**
9. PPP Trigger Mode: **Always On**
10. Internet Account: **(your NOW account ID)@nownz.co.nz**
11. Internet Password: **password123**
12. PPP Service Name: **(Left Blank)**
13. IP Protocol Version: **IPV4**
14. Static DNS: **Unticked**
15. Click: **Save**



Basic Information

Enable connection:

Name:

Service type: INTERNET TR069 VOICE Other

Connection type:

MRU:

MSS:

NAT type:

Link Information

Enable VLAN:

VLAN ID:

802.1p:

PPP Information

PPP authentication mode:

PPP trigger mode: Always online Dial manually Dial on demand

Internet account:

Internet password:

PPP service name:

IP Information

IP protocol version:

Static DNS: