

## Asus RT-AC66/88U Fibre configuration

Ensure the Router is connected from **WAN** on **Router** to **GE1** on **ONT**.

Log into the gateway:

1. Ensure your device is connected to the Router (preferably via cable)
2. Open a web browser
3. Type the following in the address bar at the top: **192.168.1.1**
4. Default Username: **admin**
5. Default Password: **admin**

This should then give access to the routers user interface.\*\*

\*\* (If the password is incorrect you will need to Factory Reset the router by pushing the Inset Reset button on the back for 10 seconds)

How to add correct settings for the NOW network:

1. From the menu on the left select: **WAN** (Under Advanced Settings)

Change the following Settings:

1. WAN Connection Type: **PPPoE**
2. Enable WAN: **Yes**
3. Enable NAT: **Yes**
4. Enable UPnP: **Yes**
5. Get The WAN IP Automatially: **Yes**
6. Connect to DNS Server Automatically: **Yes**
7. User Name: **(your NOW account ID)@nownz.co.nz**
8. Password: **password**
9. MTU: **1492**
10. MRU: **1492**
11. All else can be left unchanged
12. Select: **Apply**



The Router should now Reboot

You should now be connected to Fibre!

If you have no internet access, give NOW Techncial Support a call.

ASUS RT-AC66U Logout Reboot English

Operation Mode: **wireless router** Firmware Version: **3.0.0.4.372.67** SSID: **ASUS ASUS\_5G**

Internet Connection | Port Trigger | Virtual Server / Port Forwarding | DMZ | DDNS | NAT Passthrough

**WAN - Internet Connection**

RT-AC66U supports several connection types to WAN (wide area network). These types are selected from the dropdown menu beside WAN Connection Type. The setting fields differ depending on the connection type you selected.

Basic Config	
WAN Connection Type	PPPoE
Enable WAN	<input type="radio"/> Yes <input checked="" type="radio"/> No
Enable NAT	<input type="radio"/> Yes <input checked="" type="radio"/> No
Enable UPnP <a href="#">UPnP_FAQ</a>	<input type="radio"/> Yes <input checked="" type="radio"/> No
WAN IP Setting	
Get the WAN IP automatically	<input type="radio"/> Yes <input checked="" type="radio"/> No
WAN DNS Setting	
Connect to DNS Server automatically	<input type="radio"/> Yes <input checked="" type="radio"/> No
Account Setting	
User Name	(your NOW account ID)@nownz.co.nz
Password	password <input checked="" type="checkbox"/> Show password
Idle Disconnect Time in seconds: Disconnect after time of inactivity (in seconds)	0
MTU	1492
MRU	1492
Service Name	
Access Concentrator Name	
Additional pppd options	
Special Requirement from ISP	
Enable VPN + DHCP Connection	<input type="radio"/> Yes <input checked="" type="radio"/> No
Host Name	
MAC Address	<input type="text"/> <b>MAC Clone</b>

**Apply**